

DIGITAL INSULATION METER

Insulation is subject to many effects which can cause it to fail, including mechanical damage, vibration, excessive heat or cold, dirt, oil, corrosive vapors, moisture or humidity. The IDEAL Digital Insulation Meter is the tool every professional needs to determine whether the insulation is performing at an effective and safe level. During installation or routine maintenance, the Digital Insulation Meter identifies capacitive, absorption and leakage current, helping to prevent problems before they result in injury or equipment failure.

Industrial/Commercial

61-797 Features

- · Test voltages at 50/100/250/500/1000V
- · Perfect for testing low voltage cable
- · Automatic calculation of PI and DAR
- Auto sensing AC/DC voltage to 600V
- Low Pass Filter filters out high frequency noise
- · Earth-bond resistance
- Test inhibition if >30V
- · Digital reading with analog arc
- · Compare pass/fail mode
- · Remote test probe
- Store/recall memory
- · Auto discharge
- Auto power off
- · Backlit display auto sensing
- Low battery indication
- · Carrying case included
- · CAT IV 600V
- · 2-year warranty

61-797 Specifications

Test Voltages	50/100/250/500/1000 VDC
Voltage AC/DC	0.1-600.0V
Insulation Resistance	Up to 20GΩ
Low Resistance Test	0.01Ω to 40.00K
	t to the second

Note: This is not a ground rod tester.

TEST R V Live voltage hazard indicator O/1000 VDC COMP STORE TEST R V COMP STORE SOV 100V 250V OFF CAT TV GOOV COMP STORE COMP COMP

Alligator clips twist onto test leads



two-handed operation

Backlit display

auto sensor

Protective rubber boot





Residential/Light Commercial

61-795 Specifications

Test Voltages	250/500/1000 VDC
Voltage AC/DC	0.1-600.0V
Continuity	0.01-20.0Ω
Insulation Resistance	Up to 4000MΩ
Resistance	0.01 to 19.99 Ω and 0.1 to 199.9 Ω

61-795 Features

Test voltages: $250/500/1000V \cdot \text{Test}$ inhibition if $>25V \cdot \text{Default}$ voltmeter to $600V \cdot \text{AC/DC} \cdot \text{Backlight} \cdot \text{Digital}$ display with analog arc $\cdot \text{Auto}$ discharge $\cdot \text{Auto}$ power off $\cdot \text{Continuity} \cdot \text{Low}$ battery indication $\cdot \text{Carrying}$ case included $\cdot \text{CAT IV} - 600V \cdot 2$ -year warranty





Great for troubleshooting AFCI breaker tripping





IDEAL INDUSTRIES, INC.

1800 S. Prairie, Sycamore, IL 60178, USA / 815-895-5181 · 800-435-0705 in USA