

Catalog No. THQL1115DF



Description BRKR AFCI/GFCI 15A 1P 120V 10K PLUG-IN

UPC No 783164532081

Products > Circuit Breakers > Molded Case Circuit Breakers > Q-Line (Plug-In)

GE's Dual Function Circuit Interrupter (DFCI) provides ground fault and arc fault circuit protection in one unit. The 2014 National Electric Code mandated Ground Fault and Arc Fault circuit protection on many 15 and 20 amp kitchen and laundry circuits. Our DFCI offers both Ground Fault and Combination Arc Fault (GFCI and AFCI) protection in a simple to apply and cost-effective package.

Specifications

Descriptors

Category	Q-Line (Plug-In)
----------	------------------

Specifications

Trip Style	Non-Interchangeable
Frame Type	Q-Line
Amperage	15 A
Poles	1
System Voltage	120 Vac
120 Vac Interrupting Rating	10 KAIC
Trip Function	LI AFCI and GFCI
Continuous Current Rated	Standard
Long Time	Fixed
Current Metering	No
Protective Relays	No
Special Markings	HACR, SWD
Wire Range (Cu/Al)	#14-8 AWG
GSA Compliance	No

Classifications

UL File #	E471742
-----------	---------

Publications

Title	Publication No.	Publication Type
Residential Electronic Circuit Interrupters Revision B. 8 pages. Includes our: Dual Function Circuit Interrupter (DFCI); Combination Arc Fault Circuit Interrupter (AFCI); and Self-Test Ground Fault Circuit Interrupter (GFCI). Combination Arc Fault Circuit Interrupter (DFCI)	DET-838	Brochures
4 pages. Installation Instructions in english, french and spanish.	DEI-008	Installation and Instruction
Additional Documentation: Visit our Publication Library to find technical documentation, time current curves, CSI Specifications and promotional literature.		